Information Processing Apparatus for and Method of

Transmitting and/or Receiving Broadcast Signal

BACKGROUND OF THE INVENTION

5   Field of the Invention

The present invention relates to an information

processing apparatus and method and, more particularly,

to an information processing apparatus for and method

of processing information with a description format

10   used in a multimedia network.

Related Background Art

In recent years, as a method of using FM radio

broadcast, a so-called "visible radio receiver (a radio

receiver that can display received character

15   information) which receives character information

together with an FM audio signal using a broadcast wave

is commercially available. A device of this type has

high portability and a very simple circuit, and can

receive various kinds of information as long as it can

20   receive an FM wave.

Recently, the information transmitted using FM

audio broadcast include news, weather forecasts, and

the like. Although such information can be received

via a so-called multimedia network, they can be more

25   easily obtained by the "visible radio receiver". The

"visible radio receiver" has higher portability than

normal multimedia terminals.

However, such receiver can only receive simple character information such as weather forecast information and the like as currently available services, but can neither receive nor store information in a description format used in a multimedia network, which format can be easily handled by a personal computer (PC), in addition to the character information.

Normal data or data that can be processed by a PC may be transmitted in place of the character information. However, when such data is merely broadcasted in place of the character information, its reliability cannot be maintained, and this results in unwanted confusion upon processing of such data.

Such data may be transmitted in a system quite different from the current broadcast. However, the existing system itself must then be reexamined, and this is impractical. Also, the broadcasting station requires considerably large-scale equipment.

Furthermore, when the above-mentioned portable receiver receives such data in addition to the character information, not only the data cannot be effectively used, but also power savings and compactness required for a portable equipment for processing such two different kinds of information may be disturbed.

When digital data is transmitted using a broadcast wave, the transmission efficiency largely depends on the weather conditions and the like, and the data may often suffer so many error data. In such case, a

5　certain user may not need to acquire such data (he or she places an importance on data accuracy), but another user may want to acquire the data even if the data contain many error data (he or she places an importance on data acquisition).

10

SUMMARY OF THE INVENTION

The present invention has been made in consideration of the above situation, and has as its object to provide a novel information processing

15　apparatus and method, which can multiplex data, which can be easily processed by a versatile processor, on a broadcast signal and can transmit the multiplexed signal with high reliability and without requiring large-scale equipment.

20　In order to achieve the above object, according to one preferred embodiment of the present invention, there is provided an information processing apparatus/method which error detection or correction encodes information to be distributed in a description

25　format used in a multimedia network, and

which error detection or correction encodes at least a portion in a header in the information to be

distributed with higher redundancy than an entity in the information to be distributed, multiplexes the encoded information to be distributed in a broadcast signal, and transmits the multiplexed signal.

5   According to one preferred embodiment of the present invention, there is provided an information processing apparatus/method which inputs information to be distributed in a description format used in a multimedia network, multiplexes the information to be

10   distributed in a broadcast signal, and transmits the multiplexed signal, and

which transmits a portion of a header in the information to be distributed at least a plurality of number of times while an entity in the information to

15   be distributed is transmitted.

According to one preferred embodiment of the present invention, there is provided an information processing apparatus/method which error detection or correction encodes information to be distributed in a

20   description format used in a multimedia network, multiplexes the encoded information to be distributed in a broadcast signal, and transmits the multiplexed signal, and

which can transmit a plurality of kinds of

25   information as an entity in the information to be distributed, and uses different error detection or

correction ability in correspondence with the kind of information.

According to one preferred embodiment of the present invention, there is provided an information processing apparatus/method which inputs information to be distributed in a description format used in a multimedia network, multiplexes the information to be distributed in a broadcast signal, and transmits the multiplexed signal, and

in which the information to be distributed is transmitted as an entity in a data format used for multiplexing another information in a description format, which is not used in the multimedia network, in an FM audio signal, the data format forms an error correction code, and a header of the information to be distributed forms an error correction code different from the error correction code.

It is another object of the present invention to provide a novel information processing apparatus and method which can effectively receive and use information that can be easily processed by a versatile processor in addition to information multiplexed beforehand on a broadcast signal, and never disturb a size reduction and energy reduction.

In order to achieve the above object, according to one preferred embodiment of the present invention, there is provided an information processing

apparatus/method which receives a broadcast signal

obtained by multiplexing information to be distributed

in a description format used in a multimedia network

and an error correction or detection check code added

5   for at least partial information of the information to

be distributed, as an entity of a data format which is

used for multiplexing predetermined information in an

FM audio signal and includes an error correction check

code, and performs an error correction or detection

10   processing of the information to be distributed using

the error correction check code and the error

correction or detection check code, and

which executes the processing based on the error

correction check code and processing based on the error

15   correction or detection check code at different

timings.

According to one preferred embodiment of the

present invention, there is provided an information

processing apparatus/method which receives a broadcast

20   signal obtained by multiplexing information to be

distributed in a description format, used in a

multimedia network, as an entity of a data format used

for multiplexing predetermined information in an FM

audio signal, and stores the information to be

25   distributed in storage means, and

which informs that the received information to be distributed is stored in the storage means and is not output to an external device.

According to one preferred embodiment of the present invention, there is provided an information processing apparatus/method which receives a broadcast signal obtained by multiplexing information to be distributed in a description format, used in a multimedia network, as an entity of a data format used for multiplexing first character information in an FM audio signal, and displays second character information using display means for displaying the first character information when the information to be distributed has the second character information.

According to one preferred embodiment of the present invention, there is provided an information processing apparatus/method which receives a broadcast signal obtained by multiplexing information to be distributed in a description format, used in a multimedia network, as an entity of a data format used for multiplexing character information in an FM audio signal, and stores the information to be distributed in storage means, and

which executes a command for displaying information stored in the storage means, and a command for outputting the stored information to an external device at different timings.

It is still another object of the present invention to provide an information processing apparatus and method which can process received data as the user desired even when information transmission,

5   the transmission efficiency of which depends on the weather conditions and the like, is made.

In order to achieve the above object, according to one preferred embodiment of the present invention, there is provided an information processing

10   apparatus/method which inputs information data, and a check code for correcting an error of the information data, detects an error state of the information data, sets an allowable error state of the information data, and controls processing for the input information data

15   in accordance with results in the setting step and the detection step.

Other objects, features and advantages of the invention will become apparent from the following detailed description taken in conjunction with the

20   accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a schematic block diagram showing the arrangement of a broadcast signal transmitter according

25   to the present invention;

Fig. 2 is a graph showing the frequency spectrum allocation of a signal to be transmitted by the transmitter shown in Fig. 1 before FM modulation;

Fig. 3 shows the data format of teletext, which is
5   conventionally used;

Fig. 4 shows the format of a prefix field shown in Fig. 3 in more detail;

Fig. 5 shows the data format of HTML data transmitted by the transmitter shown in Fig. 1;

10   Figs. 6A, 6B and 6C respectively show the formats of HTML header, character data, and image data to be transmitted according to the format shown in Fig. 5 in more detail;

Fig. 7 shows the data format according to the
15   transmission order to be transmitted by the transmitter shown in Fig. 1;

Fig. 8 is a flow chart showing the operation of the transmitter shown in Fig. 1;

Fig. 9 is a schematic view showing the arrangement
20   of a receiving system that receives the data transmitted by the transmitter shown in Fig. 1;

Fig. 10 is a perspective view showing the outer appearance of a receiver 1002;

Fig. 11 is a block diagram showing the internal
25   arrangement of the receiver 1002;

Fig. 12 is a flow chart for explaining the operation of the receiver 1002 upon reception of HTML data;

Fig. 13 is a flow chart for explaining operation upon operation of a display command switch on the receiver 1002;

Fig. 14 is a flow chart for explaining operation upon operation of an external output command switch on the receiver 1002;

Fig. 15 is a block diagram showing the internal arrangement of a computer 1001; and

Fig. 16 is a flow chart for explaining reception executed when the computer 1001 receives data from the receiver 1002.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Fig. 1 is a schematic block diagram showing the arrangement of a broadcast signal transmitter according to the present invention, and shows the transmitter which is equipped in a radio broadcasting station.

Referring to Fig. 1, a personal computer (PC) 3 has an operation unit 1 and display unit 2. This PC is connected to a bus B, and can receive data from this bus B. Also, an image memory 4, format memory 5, Internet server 6, JPEG encoder 7, HTML (HyperText Markup Language) memory 8, error correction code (ECC) encoder 9, and the like are connected to the bus B.

As audio signals which are input from various types of known audio equipment and to be FM-broadcasted, stereophonic audio signals including right (R) and left (L) signals, monaural (M) signal,

5 and the like are assumed. In Fig. 1, a matrix circuit 11 receives R and L signals, and outputs their sum signal (L + R) and difference signal (L - R). The sum signal (L + R) is input to one input terminal of a switch 12. The other input terminal of this switch 12

10 receives a monaural signal (M), and outputs the monaural signal (M) in case of monaural broadcast or the sum signal (L + R) in case of stereophonic broadcast.

A pilot signal generation circuit 16 generates a

15 pilot signal of a predetermined frequency in response to switching of the switch 12. On the other hand, the frequency of the difference signal (L - R) is converted by a balanced modulation (BM) circuit 13, and is multiplexed on the output from the switch 12 and the

20 pilot signal by a multiplexing circuit 17. The frequency allocations of the individual signals will be explained below with reference to Fig. 2.

As shown in Fig. 2, the sum signal (L + R) or monaural signal (M) is allocated at the baseband side,

25 and the difference signal (L - R) is frequency-converted by a carrier wave of 38 kHz using the BM circuit 13 and is allocated in a frequency band

shown in Fig. 2. Although not shown, a bandpass filter (BPS) for cutting off unwanted frequency bands is inserted at the output stage of the BM circuit 13.

5   In this embodiment, digital data is input to a D/A converter 14 via the above-mentioned bus B, and is converted into a binary analog signal. Furthermore, this analog signal is input to a BM circuit 15 and is frequency-converted by a carrier wave of 76 kHz to allocate it at a frequency higher than those of the

10 audio signals and pilot signal. The multiplexing circuit 17 can frequency-multiplex that analog signal and other signals. The multiplexed signal is originally standardized for teletext data, and this embodiment discloses an example of a technique for

15 transmitting data in the HTML format used in a WWW (World Wide Web) as a broadcast wave, using this multiplexed signal.

The data format of teletext using a conventional FM radio broadcast wave will be explained below with

20 reference to Fig. 3. As shown in Fig. 3, in data in a matrix format, a 16-bit prefix field, 160-bit character data, and a 14-bit CRC code follow a 16-bit block identification code, and an 82-bit parity check code is added for a total of 190 bits of the prefix field,

25 character data, and CRC code, thus forming an error correction code having a code length of 272 bits.

Note that the block identification code is
assigned as sync data for identifying the block
boundary, and the location of a block is identified by
this code to establish block synchronization. The

5   16-bit prefix field has the format shown in Fig. 4, and
contains 4-bit service identification data, 1-bit
decoding identification data, 1-bit information end
data, 2-bit update data, a 4-bit data group number, and
a 4-bit data packet number.

10   The service identification data indicates the
contents of a teletext service, i.e., the type
(character, figure information, additional information,
auxiliary signal, operation signal) of the program
contents and transmission mode. Ten kinds of services

15   have already been defined as the service identification
data in the teletext, and the remaining six kinds
remain undefined. Hence, in this embodiment, a service
for broadcasting data in the HTML format is defined as
one of these six kinds. In practice, "0111", "1000",

20   "1001", "1010", and the like are undefined data.

Note that the decoding identification data
distinguishes between a case wherein error correction
requires decoding in the row direction in Fig. 3 alone,
and a case wherein error correction requires decoding

25   of the product code in the row and column directions.
The information end data identifies whether or not the
block of interest is the last block of each data group,

and the update data indicates the number of times of update of the contents of the data group of interest.

In this embodiment, in the prefix field, the service identification bit indicates that the data group of interest is a program of data in the HTML format, and whether or not the data group of interest has been updated for data of the identical previous group using the update data.

Fig. 5 shows the format of data to be transmitted in this embodiment, which format complies with that of the teletext. As shown in Fig. 5, 4-bit identification data (DID) follows immediately after a prefix field. This data DID indicates if data of the block of interest is character data complying with the HTML format, image data, a header, or the like, and also defines its compression method if the character data or image data is compressed data. If this data DID suffers errors during transmission, nonsense data is reconstructed. Hence, in this embodiment, in order to reliably detect if this 4-bit identification code has suffered code errors during transmission, a dedicated CRC code is added after this identification data DID, thus reliably detecting code errors in the identification data.

As shown in Fig. 5, 168-bit actual data can be transmitted in each block. In this embodiment, an HTML header field, character data, and image data have

different data formats. Figs. 6A to 6C show these data

formats. As shown in Fig. 6A, in a block used for

transmitting the HTML header, 32 bits of the 168-bit

data are assigned to parity that forms an error

5   correction code independently of the 82-bit parity

shown in Fig. 5. More specifically, the

above-mentioned 82-bit parity is added to 190-bit

information data to form a 272-bit error correction

code, but this 32-bit parity is added to a 16-bit

10   program code, 16-bit packet code, and 104-bit HTML

header to form a 168-bit error correction code.

Since all the program code, packet code, HTML

header, and parity are integer multiples of 8 bits, a

known Reed-Solomon code that can be processed in units

15   of 8 bits can be used as the 168-bit error correction

code using the 32-bit parity. In this way, using the

error correction code that allows processing in units

of 8 bits, a short processing time, circuit scale

reduction, and the like can be realized.

20   The program code is data which is the same as the

data group number in the teletext, and defines the

program number (of one of 2^{16} programs) of HTML data to

be broadcasted. The packet code indicates the serial

number in each program of each data block (packet), and

25   can add one of 2^{16} numbers so that packet numbers can be

assigned to a considerably long document or very

sophisticated image.

A block (packet) containing actual information data (entity) such as character data, image data, and the like will be described below. As is well known, even when image data suffers code errors on the

5 transmission path, a sufficiently visible image can be reclaimed as long as data of pixels that neighbor those corresponding to error data can be recovered. In consideration of this advantage of image data and its originally large data volume, image data can be

10 transmitted using all the 134 bits, as shown in Fig. 6C.

On the other hand, as for character data, in order to avoid characters themselves from becoming nonsense upon error correction by the above-mentioned 82-bit

15 parity, a 14-bit CRC code which is the same as that used in known teletext is added. In this fashion, using the same CRC format as in known teletext, existing resources can be effectively used, and normal teletext data and HTML data according to this

20 embodiment can be transmitted using a common circuit.

The data volume to be actually transmitted will be explained below. As the headers of HTML data, a request method, general message header (general header), request header, response header, entity

25 header, and the like are known. As may be apparent from the above description, a broadcast application

like in this embodiment requires at least a general

header, response header, and entity header.

In this embodiment, header data to be sent include

Date (generation date and time of a message) as a

5   general header, Server (server software name) and

WWW-Authenticate (authentication method used when the

server uses an authentication mechanism) as a response

header, Content-length (entity body size),

Content-Encoding (schemes of compressing, encrypting,

10   and packaging an object), Content-Transfer-Encoding

(encode scheme used upon actual data transfer), and the

like as the entity headers. The data volume to be sent

amounts to 100 characters as 8-bit alphabet data, i.e.,

about 800 bits. The data volume of this header field

15   varies depending on programs. As shown in Fig. 6A,

since 104-bit data can be transmitted per block, the

data volume of the headers roughly amounts to less than

10 blocks.

On the other hand, the data volume of character

20   data also varies depending on the length of one

program. For example, assuming that a device has a

display LCD screen size of approximately 480 × 240

dots, each of which is 0.24 mm, and displays 12-point

(5 mm × 5 mm) font data, character data for nearly 23 ×

25   11 characters are to be sent per frame. In this case,

the required data volume is 4,048 bits (= 16 × 23 × 11)

if Japanese text is expressed by JIS codes, and 33 to

34 blocks are required according to the format shown in Fig. 6B. A standard A4 document requires 19,200 bits (= 16 × 40 × 30), approximately 160 blocks. Since the data matrix that forms a single product code shown in

5 Fig. 5 can transmit data of 190 blocks, the above-mentioned HTML header data and character data for nearly an A4 size occupies roughly one matrix.

Image data will be explained below. As for image data, when a signal corresponding to one field of a

10 normal television signal such as an NTSC signal is to be transmitted, the number of pixels is, e.g., 76,800 pixels (= 240 × 320). In this case, assuming that all the pixels are quantized by 8 bits per pixel for a luminance signal Y, and pixels are sub-sampled to 1/4

15 and are then quantized by 8 bits per pixel for two different chrominance signals Cb and Cr, the total number of bits before compression coding is (76,800 + 76,800/4 + 76,800/4) × 8, i.e., 384 kbits. In this embodiment, this data is compressed to about 50 kbits

20 by JPEG, as will be described later. As shown in Fig. 6C, since the volume of image data that can be transmitted per block is 174 bits, image data for one field can be transmitted using about 290 blocks.

Fig. 7 shows a data matrix obtained by rewriting

25 that shown in Fig. 5 in accordance with the order of data to be actually transmitted by the transmitter of this embodiment. The operation of the transmitter of

this embodiment will be explained below with reference
to Fig. 7, and the flow chart in Fig. 8 that shows the
operation of the computer 3.

When the user commands the computer 3 to multiplex
5 HTML data on a broadcast signal by operating the
operation unit 1, the computer 3 displays a guidance on
the display unit 2 to direct the user to input at the
operation unit 1, and starts the processing according
to Fig. 8 (step S1). The user inputs characters at the
10 operation unit 1 or calls a desired HTML file from the
Internet server 6 and stores it in the HTML memory 8
via the bus B while observing the guidance on the
display unit 2. When the user wants to input image
data, he or she calls desired screen data from the
15 Internet server 6 as bitmap data, and stores it in the
image memory 4 via the bus B. Since this series of
operations are not directly associated with the present
invention, they are summarized as an input subroutine
(step S2) in the flow chart in Fig. 8.

20 Upon completion of storage of data in the image
memory 4 and HTML memory 8, HTML header data stored in
the HTML memory 8 is transferred to the ECC encoder 9
in accordance with an instruction from the computer 3
to start formation of 32-bit parity for a 104-bit
25 header shown in Fig. 6C (step S3). The ECC encoder 9
incorporates a 16-bit RISC processor and the like, and
can form an error correction code without any

processing by the computer 3. Hence, while the computer 3 is executing the processing in step S4 and the subsequent steps in the flow chart in Fig. 8, the ECC encoder 9 parallelly calculates parity.

5   If character data is stored (step S4), processing for adding a 14-bit CRC code to 122-bit character data in Fig. 6B is done in the computer 3 (step S5). On the other hand, if image data is stored (step S6), the processing for adding the CRC code is interrupted, and

10   image data stored in the image memory 4 is supplied to the JPEG encoder 7 and is compressed by JPEG (step S7). Note that this JPEG encoder 7 comprises a hardware chip, and can process parallel to the CRC formation in step S5.

15   When JPEG compression starts, the JPEG-compressed data, HTML header data with parity, character data added with a CRC code, and the like begin to be written in the format memory 5 (step S8). In the format memory 5, the individual data are written at locations

20   according to the transmission format shown in Fig. 7.

As shown in Fig. 7, transmission starts from blocks that store the header. Of the 272 blocks in the transmission data matrix shown in Fig. 7, the first 13 blocks and the 137th to 149th blocks sent include only

25   data blocks without any parity blocks. Blocks including the header data are successively transmitted from the first and 137th blocks, and when the data

volume including the header exceeds 136 blocks, the header blocks are transmitted repetitively. In this way, in this embodiment, since the HTML header is transmitted as early as possible, and is sent

5   respectively for a file with a large volume, the receiver side can obtain HTML header data with higher reliability earlier.

If it is detected in step S9 in Fig. 8 that all the data have been written in the format memory 5, the

10   ECC encoder 9 calculates an 82-bit parity for 190-bit data including an HTML data header and 32-bit parity stored in the format memory 5 and a 288-bit data block obtained by adding a block identification code to these 272 bits is output in step S10. Note that the 190-bit

15   data includes a group identification code (DID), 2-bit CRC, 16-bit program code (PGC), packet code (PKC), the above-mentioned prefix (PFX), and the like, as shown in Fig. 6A.

Upon completion of transmission of one header

20   block, the internal counter (not shown) of the computer 3 is counted up to count the number of transmitted blocks. Upon completion of the header data (step S11), image or character data blocks are transmitted (step S12). In Fig. 7, character data blocks are sent first,

25   which are followed by image data blocks. However, this transmission order depends on the configuration of the HTML file to be actually transmitted.

To restate, only data blocks are continuously transmitted until the 13th block, and no parity block is transmitted. However, after the 14th block, one parity block is transmitted every third block. More specifically, when it is detected based on the above-mentioned count value in step S13 that the next block to be transmitted is the 14th or 150th block, another internal counter in the computer 3 is incremented. If another two data blocks (image or character data) have been transmitted (step S14) based on the count value, a parity block is transmitted (step S15). As for such parity blocks, the ECC encoder 9 starts calculations upon completion of data write in the format memory in step S9, and the calculated parity data are sequentially written in the format memory 5.

After the parity block is transmitted, it is checked if the next block to be transmitted is the first or 137th block in the data matrix shown in Fig. 7 (step S16). If NO in step S16, it is checked if the data to be transmitted has come to an end (step S17). If NO in step S17, transmission of two blocks and one parity blocks repeats itself in steps S12 to S15.

If the next block to be transmitted is the first or 137th block, the flow returns to step S10 to successively transmit header blocks again. This operation repeats itself until it is detected in step S17 that the data to be transmitted has come to an end.

When there is no more data to send, the processing ends (step S18). In such way, the transmission data which are sequentially output from the bus B to the D/A converter 14 according to the data format shown in

5   Fig. 7 are multiplexed with an FM audio signal by the multiplexing circuit 17, as described above, and the multiplexed signal is FM-modulated by a broadcast carrier using an FM modulation circuit 18. The modulated signal is then transmitted as a broadcast

10   wave via a transmission control circuit 19.

As described above, the transmitter of this embodiment can transmit HTML data while maintaining compatibility with the character data transmission function of a conventional FM radio broadcast. Also,

15   in this embodiment, an error correction code is added by setting the redundancy of the HTML header higher than other data, and the error correction code used in conventional teletext is also used. Hence, the header of HTML data can have reliability equivalent to that

20   obtained when the HTML data is transmitted via another network. Furthermore, burst errors unique to a broadcast wave can be coped with by transmitting the header a plurality of number of times, and high reliability can be assured as a whole.

25   Since different error detection or correction redundancies are used for the image and character data, the required data can be transmitted with minimum

redundancy, and high reliability can be guaranteed as a whole.

A receiver of the present invention which receives the above-mentioned broadcast signal will be described in detail below.

5

Fig. 9 shows the schematic arrangement of a reception system that receives data transmitted by the transmitter shown in Fig. 1.

In Fig. 9, the system includes an FM broadcasting

10 station 1000, a portable computer 1001 such as a sub notebook personal computer, or the like, and a portable receiver 1002 having an FM broadcast reception function. The portable receiver 1002 comprises an interface complying with PCMCIA (which is an

15 international standard for memory cards and I/O cards (modem, LAN, and SCSI cards, and the like), and can be connected to a personal computer.

Information data transmitted by means of an FM broadcast wave from the FM broadcasting station 1000 is

20 received by the portable receiver 1002, which decodes and displays the received data. When the portable receiver 1002 is connected to the portable computer 1001, the received information data is decoded by the portable computer 1001 and is displayed on a display

25 unit or is stored in a recording medium.

Fig. 10 is a perspective view showing the outer appearance of the portable receiver 1001.

In Fig. 10, a portable receiver main body 101 has manual operation keys 102, 103, and 104 which are respectively used for issuing a display command and external output command, and selecting a broadcasting

5   station. These keys correspond to an operation unit 98 shown in Fig. 11 (to be described later). The main body 101 also has a retractable antenna 51, a pair of loudspeakers 93 and 94 which can output stereophonic audio signals, a flat panel display 96, an external

10   interface 80 complying with PCMCIA, and an indicator 99 indicating that HTML format data which has not been output to external equipment is stored in the main body after reception.

Fig. 11 is a block diagram showing the internal
15   arrangement of the portable receiver 1001.

The processing executed when the receiver 1001 outputs an FM broadcast radio audio signal to the loudspeakers 93 and 94 will be explained below. Note that a desired broadcasting station is selected by the

20   operation unit 98.

In Fig. 11, a broadcast wave received at the antenna 51 is tuned by a reception unit 52, and is detected by an FM detection circuit 53 to be converted into a multiplexed signal shown in Fig. 2. A bandpass

25   filter (BPF) 54 separates the above-mentioned pilot signal, and supplies the separated pilot signal to a detection circuit 55. The output from the detection

circuit 55 is compared with a predetermined threshold value by a comparison circuit 56, thus determining based on the comparison result if the broadcasted audio signal is a stereophonic or monaural signal.

5   On the other hand, a low-pass filter (LPF) 60 extracts a baseband signal shown in Fig. 2, and supplies the extracted signal to a matrix circuit 59 as a monaural signal or the sum signal of stereophonic audio signals. A BPF 57 extracts a signal carried by a

10 carrier wave of 38 kHz, and the extracted signal is converted to a baseband signal, i.e., the difference signal of the stereophonic audio signals by a balanced modulation (BM) circuit 58. After that, the difference signal is supplied to the matrix circuit 59. When a

15 stereophonic broadcast wave is received, the matrix circuit 59 outputs right (R) and left (L) signals of the stereophonic audio signals, and these signals are output via switches 61 and 62 controlled by the output from the comparison circuit 56.

20   On the other hand, when a monaural broadcast wave is received, both the switches 61 and 62 output the audio signal output from the LPF 60, thus similarly outputting monaural audio signals. The audio signals output from the switches 61 and 62 are output from the

25 loudspeakers 93 and 94 via amplifiers 91 and 92, respectively.

The above-mentioned data signal multiplexed on a carrier of 76 kHz is separated by a BPF 72, and is converted by a BM circuit 73 into a signal corresponding to a data sequence in the data format

5   shown in Fig. 7. This signal is supplied to a clock extraction circuit 71 to form free-running clocks, and is converted into digital data by an A/D converter 74 using these clocks. The digital data is supplied to a known data detection circuit 75 to obtain original

10 digital data. Note that the data detection circuit 75 is comprised of a known integral detection circuit, equivalent circuit, a decoding circuit using partial response, and the like.

The operation executed when the receiver of this

15 embodiment receives conventional teletext data according to the data format shown in Fig. 3 will be explained below. As described above, the conventional teletext data is also transmitted using the parity allocations shown in Fig. 7.

20 Data detected by the data detection circuit 75 are output onto a reception bus RB as a data sequence, and are stored in a reception memory 77 under the control of a CPU 81. An ECC decoding circuit 76 accesses the data in the reception memory 77 under the control of

25 the CPU 81, and performs error correction using the above-mentioned product code parity. Note that this error correction is performed using 82-bit parity in

units of data blocks, and subsequently, error

correction is performed using 82-bit parities

distributed in the vertical direction in Fig. 7.

The error-corrected character information is

5   transferred to a storage memory 78. When the user

operates the display command switch 102 (Fig. 10), the

character data in the storage memory 78 is written in a

display memory 95 while being converted into display

codes, and characters are displayed on the display 96.

10   Fig. 12 is a flow chart for explaining the

operation upon reception of the above-mentioned HTML

data by the receiver of this embodiment, and that

operation will be explained below with reference to

this flow chart.

15   When the reception unit 52 begins to receive data

(step S101), data detected by the data detection

circuit 75 are output onto the reception bus RB as a

data sequence corresponding to the data format shown in

Fig. 7, and are stored in the reception memory 77 under

20   the control of the CPU 81 according to the format shown

in Fig. 7 (step S102).

When data for one line (one data block) in the

data matrix of Fig. 7 are stored in the reception

memory 77 (step S103), the ECC decoding circuit 76

25   begins to access the data in the reception memory 77

under the control of the CPU 81. More specifically,

error correction processing is executed using 82-bit

outer code parity in units of data blocks (step S104).

Note that steps S103 and S104 repeat themselves

until the entire data matrix shown in Fig. 7 is stored

5   in the reception memory. After the entire data matrix

in Fig. 7 has been stored (step S106), the ECC decoding

circuit 76 begins to access the data in the reception

memory 77 again. At this timing, error correction

processing is made using 82-bit inner code parities

10   distributed in the data matrix in Fig. 7 in the

vertical direction (step S107).

Upon completion of the processing for one data

matrix using the outer and inner code parities, the

data are transferred from the reception memory 77 to

15   the storage memory 78, and it is checked if all the

data to be received have been received (step S108). If

YES in step S108, the above-mentioned indicator 99 is

turned on, i.e., lighted (step S109), thus ending the

processing (step S110).

20   Fig. 13 is a flow chart for explaining the

operation executed upon depression of the

above-mentioned display command switch 102 when the

aforementioned HTML data are stored in the receiver of

this embodiment, and that operation will be explained

25   below with reference to this flow chart.

If the display command switch 102 is turned on

(step S121), the data stored in the storage memory 78

begin to be scanned under the control of the CPU 81 (step S122). This scan is done in units of lines, and the stored data for each line are processed under the control of the CPU 81. The CPU 81 monitors if the data

5   of each line that have been subjected to error correction processing using a product code are character data, image data, or header data. If the line data to be processed are character data (step S123), the CPU 81 supplies the line data to the ECC

10   decoding circuit 76 to detect the presence/absence of errors using a 14-bit CRC code shown in Fig. 6B (step S124). If no errors are detected, the character data are mapped into bitmap data, which are written in the display memory 95 (step S127).

15   On the other hand, if the line data to be processed are image data (step S125), since the portable receiver of this embodiment cannot display any image, characters representing image data reception are generated (step S126), and bitmap data of these

20   characters are written in the display memory 95 in step S127.

Upon completion of scanning of all the lines (step S128), the bitmap data stored in the display memory 95 are displayed as characters on the display 96 (step

25   S129), thus ending the processing (step S130). If the line data to be processed are HTML header data, since this portable receiver cannot use them, these data are

neither subjected to error correction processing nor written in the display memory 95.

Fig. 14 is a flow chart for explaining the operation executed upon depression of the external output command switch 103 when the aforementioned HTML data are stored in the receiver of this embodiment, and that operation will be explained below with reference to this flow chart.

If the external output command switch 103 is turned on (step S141), the data stored in the storage memory 78 begin to be scanned under the control of the CPU 81 (step S142). This scan is done in units of lines, and the stored data for each line are processed under the control of the CPU 81. The CPU 81 monitors if the data of each line that have been subjected to error correction processing using a product code are character data, image data, or header data.

If the line data to be processed are character data (step S143), the presence/absence of errors is detected using the 14-bit CRC code shown in Fig. 6B as in case of the display command (step S144). If no errors are detected, the character data are directly output to external equipment such as a PC in units of lines of the data matrix shown in Fig. 7 via an external I/F 80 which complies with PCMCIA (step S147).

On the other hand, if the line data to be processed are image data, the image data are output to

the PC or the like via the I/F 80 without any
processing. Furthermore, if the line data to be
processed are HTML header data (step S145), error
correction processing is performed using 32-bit parity
5   shown in Fig. 6A, and data which have been subjected to
error correction twice are output to the external
equipment in units of lines via the I/F 80.

Upon completion of scanning of all the lines (step
S148), the data matrix stored in the storage memory is
10   deleted or overwrite on this matrix is permitted, and
the indicator 99 is turned off (step S149), thus ending
the processing (step S150).

As described above, upon receiving data, upon
displaying received data, or upon outputting the
15   received data to external equipment, the portable
receiver of this embodiment performs only error
detection or correction required for each operation,
and does not perform any unnecessary processing, thus
preventing the receiver from performing unwanted
20   operations.

When data which cannot be handled by or cannot be
effectively processed by the receiver of this
embodiment are received, the received data are stored,
and the indicator which indicates that the received
25   data have not been output is turned on. Hence, the
operator can easily recognize such state, and the
received data can be prevented from being wasted.

In the receiver of this embodiment, the display device and display command switch, which are used for displaying the conventional teletext character data can be directly used for displaying characters received as

5 data in the HTML format. Hence, the above-mentioned composite functions can be implemented without increasing the receiver size.

The image data supplied to the PC are reconstructed into original image data by a JPEG

10 decoder installed in the PC, and are processed according to links recognized based on the header.

When the receiver 1002 is attached to the computer 1001, it is controlled by the computer 1001. Furthermore, the receiver 1002 comprises a power supply

15 unit 500 including an internal battery, and can be sufficiently driven by itself. However, when the receiver 1002 is attached to the computer 1001, it is driven by receiving a power supply from the computer, and the internal battery of the power supply unit 500

20 is charged.

The arrangement of the computer 1001 will be explained below.

Fig. 15 is a block diagram showing the internal arrangement of the computer 1001.

25 The portable computer 1001 is comprised of an I/F 201 having a connector which allows connection to the receiver 1002, a CPU 202 for controlling the overall

portable computer 1001, and also the receiver 1002, a display unit 203, a RAM 204 for storing received data which are received via the I/F 201, a ROM 205 which stores an application software program and the like for

5   fetching and processing information data based on an FM broadcast wave in the computer, an audio unit 206 for outputting an audio signal, and a key input unit 207 for inputting various instructions.

Reception of information data based on an FM

10   broadcast wave received from the receiver 1002 by the computer 1001 will be explained below with reference to Fig. 16.

Fig. 16 is a flow chart showing reception executed when the portable computer 1001 receives data from the

15   receiver 1002.

An application program for receiving information sent by means of an FM broadcast wave is read out from the ROM 205, and is started, thus driving the receiver 1002 (step S210).

20   Subsequently, whether FM audio data of the FM broadcast wave or multiplexed data of an FM multiplexed broadcast is to be received is selected using the key input unit (step S211). This data is transmitted to the CPU 81 of the receiver 1002 via the I/F 201.

25   If it is selected in step S211 that the multiplexed data of the FM multiplexed broadcast is to be received (step S212), the user sets an allowable

range within which multiplexed data received by the

receiver 1002 is used as information data, using the

key input unit 207. In this embodiment, an allowable

error rate of multiplexed data is set (step S213).

5   This setting data is also transmitted to the CPU 81 of

the receiver 1002 via the I/F 201. Via such setup

processing, the user can set by himself or herself if

he or she places an importance on data availability or

accuracy.

10   The CPU 81 of the receiver 1002 checks if the

received multiplexed data has an error rate equal to or

lower than the allowable error rate set at the portable

computer 1001 (step S214).

In this case, the number of error data detected by

15   the ECC decoding circuit 76 is counted to calculate the

error rate of the received data, and the calculated

error rate is compared with the set allowable error

rate.

If the calculated error rate is higher than the

20   allowable error rate, transmission of that data is

suspended, and a message indicating this is transmitted

to the portable computer 1001. The portable computer

1001 displays a warning message on its display unit

203, thus ending the flow (step S224).

25   If it is determined in step S214 that the

calculated error rate is equal to or lower than the

allowable error rate, the receiver 1002 transmits the

multiplexed data to the portable computer 1001 (step
S215), and the multiplexed data transmitted to the
portable computer 1001 is recorded in the RAM 204 (step
S216).

5   Upon completion of data recording in the RAM 204,
data decoding (for decoding HTML data or teletext
character data) is done (step S217), and the decoded
multiplexed data is displayed on the display unit 203
(step S218), thus ending the flow (step S224).

10   If reception of the multiplexed data is not set in
step S212, the receiver 1002 encodes received FM audio
data by an encoding circuit 510, and transmits the
encoded data to the computer 1001 (step S220). The
transmitted encoded FM audio data is recorded in the
15 RAM 204 (step S221).

Upon completion of data recording in the RAM 204,
the data decoding is done (step S222), and the decoded
FM audio data is output from the audio unit 206 (step
S223), thus ending the flow (step S224).

20   In other words, the foregoing description of
embodiments has been given for illustrative purposes
only and not to be construed as imposing any limitation
in every respect.

The scope of the invention is, therefore, to be
25 determined solely by the following claims and not
limited by the text of the specifications and
alterations made within a scope equivalent to the scope

of the claims fall within the true spirit and scope of the invention.